

Apex191

PENCIL CONDENSER

APPLICATIONS: Microphone Clip, Windssock, Soft Carry Bag

DESCRIPTION:

Like the popular Apex190, the Apex191's smooth response, fast attack and quiet operation ensure high quality instrument or vocal pickup. The Apex191 however will operate with either phantom power (delivered from a console or preamp) or from an internal AA battery when phantom power is not readily available.

FEATURES:

- Low Profile Pencil Condenser Microphone
- Black Low Reflective Finish
- Operates with phantom power or internal battery

SPECIFICATIONS:

| | |
|--------------------|---|
| Type | Back Electret Condenser |
| Polar Pattern | Cardioid |
| Frequency Response | 70Hz - 18kHz |
| Sensitivity | -65dB +/- 3dB |
| Impedance | 250 Ohms |
| Max SPL | 135dB |
| Phantom Power | 9V - 52V DC, 2.0mA typical |
| Battery Current | 1.0mA, typical |
| Battery Life | More than 1000 hours with premium battery (continuous use) |

POLAR PATTERN:

Cardioid

